

Metal Zinc Alloy Push Button With LED



EB-53A

What is a request to exit button?

Request to exit button or also known as a push to exit buttons. These door security products connect to access control applications that release the power to the magnetic lock to automatically unlock doors and allow free exit.

How does emergency door release work?

When and how the emergency door release is activated

When an emergency door release button is pressed. The button must be physically connected to the PACS. The button can be connected in a number of ways, which will affect how the PACS will respond to the alarm. When the fire alarm system sends an alarm signal.

Specifications

Product Name:	Push Button Switch for Access Control
Material:	Zinc Alloy
Product size:	53Lx53Wx25H (mm)
Contact output:	NO / NC/COM
Endurance test:	100,000 times
Power Supply:	0.5A / 12-24V
Applicable door type:	Surface mounted
Applicable temperature:	-20℃ ~55℃

Dimensions(mm)



EB-53



EB-53A



S4A Industrial Co., Limited

Address: The 2nd floor, Jinmin'an Industrial Zone, #529, Bulong Rd.
Bantian St. Longgang Dist. Shenzhen, PRC. CN 518131



Tel: +86 755 29450011

www.s4a-access.com